

HYKZ-IV Vacuum Degree Tester



1.1 Application

HYKZ-IV vacuum tester is applied to measure the arc interrupter vacuum degree of vacuum circuit breaker. It is to operation and all the test results could be printed by the micro printer.

1.2 Technique index

- 1) Measurement range: $10^{-5} \sim 10^{-1}$ Pa
- 2) Max measurement error:
 $10^{-5} \sim 10^{-4} < 25\%$
 $10^{-4} \sim 10^{-3} < 20\%$
 $10^{-3} \sim 10^{-2} < 20\%$
 $10^{-2} \sim 10^{-1} < 15\%$
- 3) Rated power supply: AC220V \pm 10%, 50Hz/60Hz
- 4) Environment temperature: 0~50°C
- 5) Humidity: \leq 85%RH
- 6) Size: 420×320×280mm³
- 7) Weight <10kg

